

Technical Note

197

L.F.


A.

How to Switch a Beam-Forming Network
with Minimum Disturbance
in Existing Communication Channels

2 April

Prepared for the Defense Communications Agency
under Electronic Systems Division Contract F162376-C-0007 by

THE MITRE CORPORATION



AD A02520

The work reported in this document was performed at Lincoln Laboratory, a center for research sponsored by Massachusetts Institute of Technology, for the Military Satellite Office of the Defense Communications Agency under Air Force Contract F19628-74-C-0002.

This report may be reproduced to satisfy needs of U. S. Government agencies.

This technical report has been reviewed and is approved for publication.

FOR THE COMMANDER

James C. Roache

James C. Roache, Lt. Col. USAF

Chief, Radio Lincoln Laboratory Project Office

MASSACHUSETTS INSTITUTE OF TECHNOLOGY

LINCOLN LABORATORY

ESL

TP-76

HOW TO SWITCH A BEAM-FORMING NETWORK
WITH MINIMUM DISTURBANCE
TO EXISTING COMMUNICATION CHANNELS

K. DeSIZE
A. J. SIMMONS

Group 61

TECHNICAL NOTE 1976-28

2 APR 1976

15

F11627-5-2-111

Approved for public release; distribution unlimited.

LEXINGTON

MASSACHUSETTS

207620 ✓

ABSTRACT

A beam-forming network (BIN) consisting of a tree of variable power dividers (VPD's) is typically used to divide the power among beams in a multiple-beam antenna. During the changeover from one set of beam configurations to another it is important that a user who is present in both configurations does not have his communication channel disturbed. A procedure is presented for systematically changing the VPD's, first to an intermediate configuration, and then to a final configuration, which avoids any disturbance to continuing users.

ACCESSION TM	
NTIS	Write Section <input checked="" type="checkbox"/>
DEC	But S. <input type="checkbox"/>
INDEXED	<input type="checkbox"/>
CLASSIFICATION	
BY	
RE-SECTION AVAILABILITY CODES	
AVAIL. and or SPECIAL	
A	

CONTENTS

Abstract	111
I. Introduction	1
II. Algorithm	3
III. Proof of Algorithm	6
A. Step 1	6
B. Step 2	8
C. Steps 3-5	11
D. Step 6	11
References	15

I. Introduction

Previous reports^{1,2} have described a multiple-beam antenna for satellite-to-earth communication consisting of a microwave lens fed by an array of horns. Power is divided among the horns to vary the antenna pattern at will by means of a beam-forming network (BFN) which consists of a number of variable power dividers (VPD's) in a corporate structure array. Such an antenna has potential usefulness as a satellite-borne communication antenna in a situation where coverage patterns on the earth must be changed from time to time to fit changing communication needs.

A schematic diagram of a 16-output BFN is shown in Fig. 1. Each junction in this diagram represents a variable power divider, which typically consists of two hybrid junctions and two phase shifters in a bridge circuit.³ The differential phase shift between these phase shifters is varied to vary the power division between the two output ports of the bridge.

This technical note addresses the problem of how to switch the BFN from one power distribution to another without causing the EIRP of a continuing user (one who maintains communication in both distributions) to be interrupted during the switchover. A procedure is presented for reconfiguring the BFN in such a way as to cause minimum disturbance (a drop of 3 dB or less) to such a user. The specific requirement is that a continuing user experience a drop in EIRP of no more than 3 dB below the present or new EIRP, whichever is smaller. The temporary 3 dB drop in power is to take place over a short time and allows for the use of latching ferrite phase shifters³ in the VPD's. The 3 dB value is due to the fact that when the power division of a VPD is




Fig. 1. 16-Element beam-forming network, schematic

changed, the ferrite phase shifters go through a reset-set sequence, with the reset state resulting in nominally equal power division between its output ports. Thus a 3 dB power drop can occur in certain cases for a short period of time. In order to limit this drop to a maximum of 3 dB, the VPD's must be switched one level of the BFN at a time rather than all levels simultaneously. (In the latter case the 3 dB drop could increase to $3N$ dB where N is the number of levels.)

In accordance with the above requirement, an algorithm has been devised which ensures that the power drop never exceeds 3 dB below that of the initial or final power setting of any port of the BFN, and this drop only occurs during the reset time of the ferrite phase shifter. The algorithm requires that the VPD's be set in successive levels starting from the N th level, proceeding to the first level and then back up to the N th level. The N th level is adjacent to the M -port end of a $1:M$ BFN. The first level has a single VPD; whereas the N th level has $M/2$ VPD's, where $M = 2^{N-1}$, (see Fig. 1).

II. Algorithm

N th Level through 2nd Level

1. If the total power into a VPD increases when going from the initial distribution to the final distribution, do not set the VPD to the final power division.
2. If the total power into a VPD decreases or remains constant, when going from the initial distribution to the final distribution, set the VPD to the final power division.

First Level

1. Set the single VPD to the final power division.

Second Level through Nth Level

1. Set all VPD's that have not been previously set to their final power division.


Note: At any level all of the VPD's, if of the latching ferrite variety, must go through the reset-cycle (even if their power divisions are not to be changed) in order to maintain the same insertion phase at all ports.

The use of the above algorithm requires that the total power into all VPD's (normalized to the input power to the first level VPD) first be computed for both initial and final distributions. However this must be done anyway, in order to determine the proper settings for each of the VPD's.

Utilizing Fig. 2 which shows a BFN for an 8-beam system an example of the use of the algorithm follows,

<u>Level of Switching</u>	<u>Output Power Units on Ports</u>							
	A	B	C	D	E	F	G	H
Initial	1	1	0	2	1	1	9	2
3rd Level	1	1	2	0	1	1	11/3	22/3
2nd Level	1	1	2	0	13/5	13/5	39/15	78/15
1st Level	1	1	6	0	1	1	1	2
2nd Level	11/2	11/2	1	0	1	1	1	2
3rd Level and final	1	10	1	0	1	1	1	2

In the above example it is noted that the power level on any port does not drop below the smaller of its initial or final values. If instead of this procedure, the first VPD in the 3rd level had been switched first to its final value, the power at A would have dropped by 10 dB and similarly if the 1st



NOTE: UPPER NUMBERS ARE POWER DIVISIONS FOR FINAL DISTR.
 LOWER NUMBERS ARE POWER DIVISIONS FOR INITIAL DISTR.

Fig. 2. Example of use of algorithm

level VPD had been switched first, power at ports EFG would have dropped by 4 dB.

III. Proof of Algorithm

In order to prove that this algorithm provides the desired results, consider a typical path through a BFN as shown in Fig. 3. (Figure 3 represents a portion of a 32-port BFN.) P_i represents the power into the typical VPD, at the $(i+1)^{th}$ level. C_i represents the power coupling coefficient of the i^{th} VPD, a number between 0 and 1, (assuming lossless VPD's) and is the number relating the coupling from one VPD to the next so that

$$P_{i+1} = C_{i+1} P_i$$

It is assumed that P_0 , the input power level, remains unchanged. We will prove the algorithm for the path shown for a 5-level BFN, and by extension this will prove it for any path through the BFN. A similar proof holds for a BFN of any number of levels. We also consider only a transmitting antenna, but the same argument holds true for a receiving antenna. Let $P_1^{(1)}$ and $C_1^{(1)}$ be the initial values of P_1 and C_1 , $P_1^{(2)}$, and $C_1^{(2)}$ be their final values. We wish to show that $P_5 \geq P_5^{(1)}$ or $P_5 \geq P_5^{(2)}$ at all times while going through the steps of the procedure.

A. Step 1

Following the rules of the algorithm, set the 5th level of VPD's:

1. If $P_4^{(1)} < P_4^{(2)}$, C_5 remains at $C_5^{(1)}$. P_5

thus remains unchanged, at its initial value.




Fig. 3. Typical path through a BFN

2. If $P_4^{(1)} \geq P_4^{(2)}$, set C_5 to its new value, $C_5^{(2)}$.
 P_5 now becomes $P_5 = C_5^{(2)} P_4^{(1)} \geq C_5^{(2)} P_4^{(2)} = P_5^{(2)}$, so
 P_5 is greater than or equal to its final value.

Thus in Step 1 we have satisfied the requirement. (This step is outlined in Fig. 4.)

B. Step 2


Set the 4th level of VPD's.

1. If $P_3^{(1)} < P_3^{(2)}$, C_4 remains unchanged at $C_4^{(1)}$, and thus P_4 remains at $P_4^{(1)}$. We have changed nothing at this step so P_5 is unchanged.

2. If $P_3^{(1)} \geq P_3^{(2)}$, change C_4 to $C_4^{(2)}$. P_4 then takes on an intermediate value, $P_4^I = C_4^{(2)} P_3^{(1)} \geq C_4^{(2)} P_3^{(2)} = P_4^{(2)}$. If $C_4^{(2)} \geq C_4^{(1)}$ then $P_4^I \geq P_4^{(1)}$ and P_5 is thus increased or remains unchanged in this step. If however $C_4^{(2)} < C_4^{(1)}$, then $P_4^I < P_4^{(1)}$, and we must have reduced P_5 in this step. However, if $P_4^I < P_4^{(1)}$, then $P_4^{(2)} < P_4^{(1)}$ and thus C_5 will have been set to its new value, $C_5^{(2)}$, in Step 1. Therefore in this step P_5 becomes $P_5 = C_5^{(2)} P_4^I \geq C_5^{(2)} P_4^{(2)} = P_5^{(2)}$, and so P_5 is greater than or equal to its final value, as desired.

(This step is outlined in Fig. 5.)

STEP 1
(Fifth Row)



•• $P_5 \geq P_5^{(1)}$ or $P_5^{(2)}$ At End of Step 1

Fig. 4. Outline of Step 1

STEP 2
Fourth Row

TN-76-20 (5)





Fig. 5. Outline of Step 2

C. Steps 3-5

Similar arguments may be carried out for setting each level of VPD's to their intermediate states. The logic for Step 3, for example, is outlined in Fig. 6.

D. Step 6

In Step 6, we start back up the tree, setting level 2 to its final value. We need only be concerned if we have not yet set C_2 to its final value, in Step 4, and if $C_2^{(2)} < C_2^{(1)}$, which would reduce P_2 and would thus reduce P_5 , possibly below the desired level. The upper part of the tree is, at this point in the procedure, set so that P_5 is at an acceptable level if $P_2 = P_2^{(1)}$, a situation which was the case just before Step 5. Thus we need only be concerned if, after this step, P_2 is reduced below $P_2^{(1)}$. The level of P_2 after this step is $P_2 = C_2^{(2)} P_1^{(2)} = P_2^{(2)}$, so we are concerned only if $P_2^{(2)} < P_2^{(1)}$. But if this is the case, then C_3 will have been set to its final value, $C_3^{(2)}$, in Step 3, and so setting C_2 in this step merely sets P_3 to its final value. The same argument now holds at level 4: We can only have a possible problem if P_3 is reduced in this step below its initial value. But if $P_3^{(2)} < P_3^{(1)}$, C_4 has already been set to its final value in Step 2, and so setting C_2 in this step will set $P_4 = P_4^{(2)}$. If $P_4^{(2)} < P_4^{(1)}$, C_5 will



•• $P_5 \geq P_5^{(1)}$ or $P_5^{(2)}$ At End of This Step

Fig. 6. Outline of Step 3


have been set to $C_5^{(2)}$, and the effect of this step will be to set P_5 to its final desired value.

This argument is outlined in Fig. 7, and a similar argument holds for each of Steps 7, 8 and 9 in which Levels 3, 4 and 5 are set to their final values.

Thus we have shown that the proposed algorithm satisfies the requirement that P_5 remains greater than or equal to its initial or final value after each step in the procedure.

STEP 6
Second Row

TH-76-20 (1)



P_5 Increases in value or is set to $P_5(2)$ in this step

Fig. 7. Outline of Step 6

References

1. A. R. Dion and L. J. Ricardi, "A Variable-Coverage Satellite Antenna System," Proc. IEEE 59, 252 (1971), DDC AD-728190.
2. L. J. Ricardi, A. J. Simmons, A. R. Dion, L. K. DeSize, and B. M. Potts, "Some Characteristics of a Communication Satellite Multiple-Beam Antenna," Technical Note 1975-38, Lincoln Laboratory, M.I.T. (23 January 1975), DDC AD-A006405/5.
3. L. K. DeSize, "Measured Characteristics of Variable Power Dividers," Technical Note 1975-38, Lincoln Laboratory, M.I.T. (27 May 1975), DDC AD-A012288/7.

OUTSIDE DISTRIBUTION LIST

Army

Lt. Colonel J. D. Thompson
ATTN: DAMO-TCS
Department of the Army
Washington, D.C. 20310

Mr. D. L. LaBanca
U.S. Army Satellite Communications
Agency
ATTN: AMCPM-SC511
Building 209
Fort Monmouth, N.J. 07703

Headquarters
Department of the Army
ATTN: DAMA-CSC
Washington, D.C. 20310

Navy

Dr. R. Connley
Office of Chief of Naval Operations
ATTN: 094H
Department of the Navy
Washington, D.C. 20350

Capt. R. E. Enright
Office of Chief of Naval Operations
Attn: 041E
Department of the Navy
Washington, D.C. 20350

Mr. D. McClure
Office of Naval Telecommunications
System Architect
3801 Nebraska Avenue
Washington, D.C. 20390

LCDR George Burman
Naval Electronics Systems Command
Headquarters
ATTN: PME-106
Department of the Navy
Washington, D.C. 20350

Marine Corps

Major G. P. Crascuolo
ATTN: CE
Headquarters, U.S. Marine Corps
Washington, D.C. 20380

Air Force

Colonel J. C. Mayers
ATTN: RDSC
Headquarters, U.S. Air Force
Washington, D.C. 20330

Lt. Colonel J. C. Wright
ATTN: PRCXP
Headquarters, U.S. Air Force
Washington, D.C. 20330

JCS

Lt. Colonel J. S. Tuck
Organization Joint Chiefs of Staff
ATTN: J-6
Washington, D.C. 20301

Mr. S. L. Stauss
Organization Joint Chiefs of Staff
ATTN: J-3
Washington, D.C. 20301

NSA

Mr. George Jelen, Jr.
National Security Agency
ATTN: S-26
Ft. George G. Meade, Md. 20755

Mr. David Bitzer
National Security Agency
ATTN: R-12
Ft. George G. Meade, Md. 20755

TRI-TAC

Mr. Paul Forrest
TRI-TAC
Ft. Monmouth, N.J. 07703

DCA

Capt. E. Nicastrì
SAMSO
P. O. Box 92960
Worldway Postal Center
Los Angeles, CA 90009
(20 copies)

C. Bredall
Aerospace Corp.
Bldg. 110, R. 1364
2400 El Segundo, Blvd.
El Segundo, CA 90045 (5 copies)

Dr. Frederick E. Bond, Code 800
Defense Communications Agency
8th Street and South Courthouse Road
Arlington, Virginia
(5 copies)

Mr. Troy Ellington
Defense Communications Eng. Center
1860 Wiehle Avenue
R-405
Reston, Virginia 22909
(2 copies)

C. Sletten
RADC/ETE
Stop 30
Hanscom Air Force Base
Bedford, Mass.

Mr. R. Donovan
Defense Communications Eng. Center
1860 Wiehle Avenue
R-405
Reston, Virginia 22090

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER ESD-TR-76-74	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) How to Switch a Beam-Forming Network with Minimum Disturbance to Existing Communication Channels		5. TYPE OF REPORT & PERIOD COVERED Technical Note
7. AUTHOR(s) Lorne K. DeSize and Alan J. Simmons		6. PERFORMING ORG. REPORT NUMBER Technical Note 1976-20
9. PERFORMING ORGANIZATION NAME AND ADDRESS Lincoln Laboratory, M.I.T. P.O. Box 73 Lexington, MA 02173		8. CONTRACT OR GRANT NUMBER(s) F19628-76-C-0002
11. CONTROLLING OFFICE NAME AND ADDRESS Defense Communications Agency 8th Street & So. Courthouse Road Arlington, VA 22204		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office) Electronic Systems Division Hanscom AFB Bedford, MA 01731		12. REPORT DATE 2 April 1976
		13. NUMBER OF PAGES 24
		15. SECURITY CLASS. (of this report) Unclassified
		15a. DECLASSIFICATION DOWNGRADING SCHEDULE
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTE None		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) beam-forming network multiple-beam antenna variable power dividers satellite communications		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) A beam-forming network (BFN) consisting of a tree of variable power dividers (VPD's) is typically used to divide the power among beams in a multiple-beam antenna. During the changeover from one set of beam configurations to another it is important that a user who is present in both configurations does not have his communication channel disturbed. A procedure is presented for systematically changing the VPD's, first to an intermediate configuration, and then to a final configuration, which avoids any disturbance to continuing users.		

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

U.S. DEPARTMENT OF COMMERCE
National Technical Information Service

AD-A025 649

PERFORMANCE EVALUATION OF NINE CANDIDATE
REMBASS SINGLE-TARGET CLASSIFIERS

ADAPTRONICS, INCORPORATED

PREPARED FOR
ARMY MOBILITY EQUIPMENT
RESEARCH AND DEVELOPMENT CENTER

20 FEBRUARY 1976

KEEP UP TO DATE

Between the time you ordered this report—which is only one of the hundreds of thousands in the NTIS information collection available to you—and the time you are reading this message, several *new* reports relevant to your interests probably have entered the collection.

Subscribe to the **Weekly Government Abstracts** series that will bring you summaries of new reports *as soon as they are received by NTIS* from the originators of the research. The WGA's are an NTIS weekly newsletter service covering the most recent research findings in 25 areas of industrial, technological, and sociological interest—invaluable information for executives and professionals who must keep up to date.

The executive and professional information service provided by NTIS in the **Weekly Government Abstracts** newsletters will give you thorough and comprehensive coverage of government-conducted or sponsored re-

search activities. And you'll get this important information within two weeks of the time it's released by originating agencies.

WGA newsletters are computer produced and electronically photocomposed to slash the time gap between the release of a report and its availability. You can learn about technical innovations immediately—and use them in the most meaningful and productive ways possible for your organization. Please request NTIS-PR-205/PCW for more information.

The weekly newsletter series will keep you current. But *learn what you have missed in the past* by ordering a computer **NTISearch** of all the research reports in your area of interest, dating as far back as 1964, if you wish. Please request NTIS-PR-186/PCN for more information.

WRITE: Managing Editor
5285 Port Royal Road
Springfield, VA 22161

Keep Up To Date With SRIM

SRIM (Selected Research in Microfiche) provides you with regular, automatic distribution of the complete texts of NTIS research reports *only* in the subject areas you select. SRIM covers almost all Government research reports by subject area and/or the originating Federal or local government agency. You may subscribe by any category or subcategory of our WGA (**Weekly Government Abstracts**) or **Government Reports Announcements and Index** categories, or to the reports issued by a particular agency such as the Department of Defense, Federal Energy Administration, or Environmental Protection Agency. Other options that will give you greater selectivity are available on request.

The cost of SRIM service is only 45¢ domestic (60¢ foreign) for each complete

microfiche report. Your SRIM service begins as soon as your order is received and processed and you will receive biweekly shipments thereafter. If you wish, your service will be backdated to furnish you microfiche of reports issued earlier.

Because of contractual arrangements with several Special Technology Groups, not all NTIS reports are distributed in the SRIM program. You will receive a notice in your microfiche shipments identifying the exceptionally priced reports not available through SRIM.

A deposit account with NTIS is required before this service can be initiated. If you have specific questions concerning this service, please call (703) 451-1558, or write NTIS, attention: SRIM Product Manager.

This information product distributed by

NTIS

U.S. DEPARTMENT OF COMMERCE
National Technical Information Service
5285 Port Royal Road
Springfield, Virginia 22161